Vented Design DIY Kits

D52-2 A





Feature:

- 5" is responsible for the mid-low and the 25mm tweeter is responsible for the high frequency. Each driver handles its own frequency ranges.
- Professional crossover design, using low-loss PP capacitors and oxygen-free copper inductance components
- DIY boxes, great fun of hands on experience by do it yourself
- Environmental- friendly design, the box structure adopts imported wood plates, no paint, no glue for assembly.
- With 50W*2CH amplifier, Class D, Bluetooth 5.0

SYSTEM SPECIFICATION

PRODUCT NUMBER

◆ SYSTEM TYPE

◆ NOMINAL IMPEDANCE

◆ FREQUENCY RESPONSE(-6dB)

◆ SENSTIVITY(1M/1W)

RATED POWER INPUT

MAXIMUM POWER INPUT

DRIVER

AMPLIFIER

CROSSOVER POINT

◆ ENCLOSURE STRUCTURE

NET WEIGHT

DIMENSIONS/BOX

PACKING

D52-2A

2.0System

8ohm

40 - 35 K Hz

90 +/- 2dB

30W

60W

W5-2143,25-1933S

AMH200-100 50W*2CH,CLASS D

3.5K Hz

17mm wood plate

4.85Kg/pc

200 W x269 D x300 H (mm) (10L)

Plain Carton



TANG BAND INDUSTRIES CO., LTD

web : www.tb-speaker.com e-mail : info@tb-speaker.com tel : +886-2-2657-0282 fax : +886-2-2658-0166

D52-2A Package include:

- 5"Full range driver 2pcs
- 25mm tweeter 2pcs
- With 50W*2CH amplifier 1pcs
- Instructions Guide
- All wood plates and accessory